

# ST2111FX

### HIGH VOLTAGE FAST-SWITCHING NPN POWER TRANSISTOR

#### Features

- NEW SERIES, ENHANCED PERFORMANCE
- FULLY INSULATED PACKAGE (U.L. COMPLIANT) FOR EASY MOUNTING
- HIGH VOLTAGE CAPABILITY (1500V)
- HIGH SWITCHING SPEED
- TIGTHER h<sub>fe</sub> CONTROL
- IMPROVED RUGGEDNESS

### Applications

 HORIZONTAL DEFLECTION AND SWITCH MODE POWER SUPPLY FOR TVs.

### Description

The device is manufactured using Diffused Collector Technology for more stable operation vs base drive circuit variations resulting in very low worst case dissipation.



### Internal Schematic Diagram



### Order codes

Part Number	Marking	Package	Packing
ST2111FX	2111FX	ISOWATT218FX	TUBE

# 1 Electrical Ratings

Symbol	Parameter	Value	Unit				
V <sub>CES</sub>	Collector-Base Voltage (v <sub>BE</sub> = 0)	1500	V				
V <sub>CEO</sub>	Collector-Emitter Voltage (I <sub>B</sub> = 0)	700	V				
V <sub>EBO</sub>	Collector-Base Voltage ( $I_C = 0$ )	7	V				
۱ <sub>C</sub>	Collector Current	12	А				
I <sub>CM</sub>	Collector Peak Current (t <sub>P</sub> < 5ms)	25	А				
Ι <sub>Β</sub>	Base Current	7	А				
P <sub>TOT</sub>	Total dissipation at $T_c = 25^{\circ}C$	65	W				
V <sub>isol</sub> Insulation Withstand Voltage (RMS) from All Three Leads to External Heatsink		2500	V				
T <sub>STG</sub>	Storage Temperature	-65 to 150	°C				
Τ <sub>J</sub>	Max. Operating Junction Temperature	150	°C				

#### Table 1. Absolute Maximum Rating

#### Table 2. Thermal Data

ſ	Symbol	Parameter	Value	Unit
	R <sub>thJ-case</sub>	Thermal Resistance Junction-Case Max	1.9	°C/W



## 2 Electrical Characteristics

Symbol	Parameter	Test Conditions	Min.	Тур.	Max.	Unit
Gymbol	i arameter			тур.	Max.	Onit
ICES	Collector Cut-off Current	V <sub>CE</sub> = 1500V			1	mA
	(V <sub>BE</sub> = 0)	V <sub>CE</sub> = 1500V, Tj=125°C			2	mA
I <sub>EBO</sub>	Emitter Cut-off Current $(I_{C} = 0)$	V <sub>EB</sub> = 7V			1	mA
V <sub>CE(sus)</sub> Note: 1	Collector-Emitter Sustaining Voltage(I <sub>B</sub> = 0)	I <sub>C</sub> = 100mA	700			V
V <sub>CE(sat)</sub> Note: 1	Collector-Emitter Saturation Voltage	$I_{\rm C} = 8  {\rm A}$ $I_{\rm B} = 2$	A		3	V
V <sub>BE(sat)</sub> Note: 1	Base-Emitter Saturation Voltage	$I_{\rm C} = 8 \text{ A}$ $I_{\rm B} = 2 \text{ A}$	Ą		1.5	V
h <sub>FE</sub>		I <sub>C</sub> = 1 A V <sub>CE</sub> = 5 V		25		
Note: 1	DC Current Gain	I <sub>C</sub> = 8 A V <sub>CE</sub> =	5V 4.5		9	
	INDUCTIVE LOAD	I <sub>C</sub> =6 A f <sub>h</sub> =64KH	łz			
t <sub>s</sub>	Storage Time	I <sub>B(on)</sub> =1 A V <sub>BE(off)</sub> :	=-2.5 V	2.3	3	μs
t <sub>f</sub>	-	L <sub>BB(off)</sub> =1.3µH		0.16	0.35	μs

Table 3.Electrical Characteristics ( $T_{CASE} = 25^{\circ}C$ ; unless otherwise specified)

Note: 1 Pulsed duration =  $300 \,\mu$ s, duty cycle  $\leq 1.5\%$ .



## 3 Package Mechanical Data

In order to meet environmental requirements, ST offers these devices in ECOPACK® packages. These packages have a Lead-free second level interconnect. The category of second level interconnect is marked on the package and on the inner box label, in compliance with JEDEC Standard JESD97. The maximum ratings related to soldering conditions are also marked on the inner box label. ECOPACK is an ST trademark. ECOPACK specifications are available at: <a href="http://www.st.com">www.st.com</a>



DIM.	mm.		
	MIN.	ТҮР	MAX.
А	5.30		5.70
С	2.80		3.20
D	3.10		3.50
D1	1.80		2.20
E	0.80		1.10
F	0.65		0.95
F2	1.80		2.20
G	10.30		11.50
G1		5.45	
н	15.30		15.70
L	9		10.20
L2	22.80		23.20
L3	26.30		26.70
L4	43.20		44.40
L5	4.30		4.70
L6	24.30		24.70
L7	14.60		15
N	1.80		2.20
R	3.80		4.20
Dia	3.40		3.80

**ISOWATT218FX MECHANICAL DATA** 



57

# 4 Revision History

Date	Revision	Changes
18-Oct-2005	1	First Issue



Information furnished is believed to be accurate and reliable. However, STMicroelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of STMicroelectronics. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. STMicroelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of STMicroelectronics.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners

© 2005 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan -Malaysia - Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com

