

Open Carrier Double-Balanced Mixer For Microwave Telecommunications

Rev. V2

Features

LO & RF: 4.0 TO 20.0 GHz

• IF: DC TO 4.0 GHz

LO DRIVE: +7 dBm (NOMINAL)
MICROSTRIP INTERFACE


Description

The MC4507 is a double balanced mixer, designed for use in military, commercial and test equipment applications. The design utilizes Schottky ring quad diodes and broadband soft dielectric and ferrite baluns to attain excellent performance. This mixer can also be used as a phase detector and/or bi-phase modulator since the IF port is DC coupled to the diodes. The use of high temperature solder and welded assembly processes used internally makes it ideal for use in manual, semi-automated assembly. Environmental screening available to MIL-STD-883, MIL-STD-202, or MIL-DTL-28837, consult factory.

Ordering Information

Part Number	Package	
MC4507	Open Carrier	
MC4507-2	Open Carrier	

Product Image



Electrical Specifications: $Z_0 = 50\Omega$ Lo = +7 dBm (Downconverter application only)


Parameter	Test Conditions	Units	Typical	Guaranteed	
Parameter	rest Conditions			+25°C	-54° to +85°C
SSB Conversion Loss (max) & SSB Noise Figure (max)	$fR=6\ to\ 18\ GHz\ ,\ fL=6\ to\ 18\ GHz\ ,\ fl=0\ to\ 2\ GHz$ $fR=6\ to\ 18\ GHz\ ,\ fL=6\ to\ 18\ GHz\ ,\ fl=0\ to\ 4\ GHz$ $fR=4\ to\ 20\ GHz\ ,\ fL=4\ to\ 20\ GHz\ ,\ fl=0\ to\ 4\ GHz$	dB dB dB	6.0 6.5 7.5	7.5 8.0 9.0	8.0 8.5 9.5
Isolation, L to R (min)	fL = 8 to 16 GHz fL = 6 to 18 GHz fL = 4 to 20 GHz	dB dB dB	35 30 20	25 18 12	23 16 10
Isolation, L to I (min)	fL = 8 to 16 GHz fL = 6 to 18 GHz fL = 4 to 20 GHz	dB dB dB	35 30 23	25 18 12	23 16 10
Isolation, R to I (min)	fL = 4 to 20 GHz	dB	35		
1 dB Conversion Comp.	fL = +7 dBm	dBm	+0		
Input IP3	fR1 = 8.4 GHz at –5 dBm, fR2 = 8.42 GHz at –5 dBm, fL = 8.6 GHz at +7 dBm fR1 = 14.4 GHz at –5 dBm, fR2 = 14.42 GHz at –5 dBm, fL = 15.4 GHz at +7 dBm	dBm dBm	+10 +11		





Open Carrier Double-Balanced Mixer For Microwave Telecommunications


Rev. V2


Typical Performance Curves




















Open Carrier Double-Balanced Mixer For Microwave Telecommunications

Rev. V2

Absolute Maximum Ratings

Parameter	Absolute Maximum		
Operating Temperature	-40°C to +85°C		
Storage Temperature	-65°C to +100°C		
Peak Input Power	+20 dBm max @ +25°C +17 dBm max @ +85°C		
Peak Input Current	50 mA DC		

Outline Drawing: Open Carrier* MC4507



*For the base model, only the IF1 port is connected. For the "-2" model, only the IF2 port is connected.

 Dimensions are inches (millimeters) ±0.015 (0.38) unless otherwise specified.

MC4507



Open Carrier Double-Balanced Mixer For Microwave Telecommunications

Rev. V2

M/A-COM Technology Solutions Inc. All rights reserved.

Information in this document is provided in connection with M/A-COM Technology Solutions Inc ("MACOM") products. These materials are provided by MACOM as a service to its customers and may be used for informational purposes only. Except as provided in MACOM's Terms and Conditions of Sale for such products or in any separate agreement related to this document, MACOM assumes no liability whatsoever. MACOM assumes no responsibility for errors or omissions in these materials. MACOM may make changes to specifications and product descriptions at any time, without notice. MACOM makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MACOM FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MACOM SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.