

# WTL16P-2416112BA00 W16

**SMALL PHOTOELECTRIC SENSORS** 





#### Ordering information

| Туре               | Part no. |
|--------------------|----------|
| WTL16P-2416112BA00 | 1220298  |

Other models and accessories → www.sick.com/W16

Illustration may differ







#### Detailed technical data

#### **Features**

| Functional principle   | Photoelectric proximity sensor                                |
|--|---|
| Functional principle detail  | Background suppression, LineSpot technology                   |
| Sensing range  |   |
| Sensing range min.   | 10 mm   |
| Sensing range max.   | 500 mm  |
| Adjustable switching threshold for background suppression                        | 100 mm 500 mm   |
| Reference object   | Object with 90% remission (based on standard white, DIN 5033) |
| Minimum distance between set sensing range and background (black 6% / white 90%) | 15 mm, at a distance of 200 mm                                |
| Recommended sensing range for the best per-<br>formance                          | 150 mm 250 mm   |
| Emitted beam   |   |
| Light source   | PinPoint LED  |
| Type of light  | Visible red light   |
| Shape of light spot  | Line-shaped   |
| Light spot size (distance)   | 3 mm x 30 mm (200 mm)   |

| Maximum dispersion of the emitted beam around the standardized transmission axis (squint angle) | < +/- 1.0° (at Ta = +23 °C)  |
|---|--|
| Key LED figures   |  |
| Normative reference   | EN 62471:2008-09   IEC 62471:2006, modified  |
| LED risk group marking  | Free group   |
| Wave length   | 635 nm   |
| Average service life  | 100,000 h at $T_a = +25  ^{\circ}\text{C}$   |
| Adjustment  |  |
| Teach-Turn adjustment   | BluePilot: For setting the sensing range   |
| IO-Link   | For configuring the sensor parameters and Smart Task functions                               |
| Indication  |  |
| LED blue  | BluePilot: sensing range indicator   |
| LED green   | Operating indicator Static on: power on Flashing: IO-Link mode                               |
| LED yellow  | Status of received light beam<br>Static on: object present<br>Static off: object not present |
| Special features  | Line-shaped light spot   |
| Special applications  | Detecting perforated objects   |
|   |  |

### Safety-related parameters

| MTTF <sub>D</sub>             | 539 years                                    |
|-------------------------------|--|
| <b>DC</b> <sub>avg</sub>      | 0 %  |
| T <sub>M</sub> (mission time) | 20 years (EN ISO 13849)<br>Rate of use: 60 % |

#### Communication interface

| Bluetooth                   | <b>√</b> , COM2 (38,4 kBaud)   |
|-----------------------------|--|
| Data transmission rate      | COM2 (38,4 kBaud)  |
| Cycle time                  | 2.3 ms   |
| Process data length         | 16 Bit   |
| Process data structure      | Bit 0 = switching signal $Q_{L1}$<br>Bit 1 = switching signal $Q_{L2}$<br>Bit 2 15 = empty |
| VendorID                    | 26   |
| DeviceID HEX                | 0x8001B4   |
| DeviceID DEC                | 8389044  |
| Compatible master port type | A  |
| SIO mode support            | Yes  |

#### Electrical data

| Supply voltage $\mathbf{U}_{\mathrm{B}}$ | 10 V DC 30 V DC <sup>1)</sup> |
|--|-------------------------------|
| Ripple                                   | ≤ 5 V <sub>pp</sub>           |

Limit values

<sup>2)</sup> Signal transit time with resistive load in switching mode.

<sup>3)</sup> With light/dark ratio 1:1.

| Usage category                        | DC-12 (According to EN 60947-5-2)<br>DC-13 (According to EN 60947-5-2)   |
|---------------------------------------|--|
| Current consumption                   | $\leq$ 30 mA, without load. At U <sub>B</sub> = 24 V   |
| Protection class                      | III  |
| Digital output                        |  |
| Number                                | 2 (Complementary)  |
| Туре                                  | Push-pull: PNP/NPN   |
| Signal voltage PNP HIGH/LOW           | Approx. U <sub>B</sub> -2.5 V / 0 V  |
| Signal voltage NPN HIGH/LOW           | Approx. $U_B / < 2.5 \text{ V}$  |
| Output current I <sub>max.</sub>      | ≤ 100 mA   |
| Circuit protection outputs            | Reverse polarity protected Overcurrent and short-circuit protected   |
| Response time                         | ≤ 500 µs <sup>2)</sup>   |
| Repeatability (response time)         | 150 μs   |
| Switching frequency                   | 1,000 Hz <sup>3)</sup>   |
| Pin/Wire assignment                   |  |
| Function of pin 4/black (BK)          | Digital output, light switching, object present $\rightarrow$ output Q <sub>L1</sub> HIGH; IO-Link communication C |
| Function of pin 4/black (BK) - detail | The pin 4 function of the sensor can be configured, Additional possible settings via IO-Link                       |
| Function of pin 2/white (WH)          | Digital output, dark switching, object present $\rightarrow$ output $\bar{Q}_{L1}\text{LOW}$                       |
| Function of pin 2/white (WH) - detail | The pin 2 function of the sensor can be configured, Additional possible settings via IO-Link                       |
|                                       |  |

<sup>&</sup>lt;sup>1)</sup> Limit values.

#### Mechanical data

| Housing  | Rectangular               |
|--|---------------------------|
| Dimensions (W x H x D)                         | 20 mm x 55.7 mm x 42 mm   |
| Connection                                     | Male connector M12, 4-pin |
| Material                                       |                           |
| Housing  | Plastic, VISTAL®          |
| Front screen                                   | Plastic, PMMA             |
| Male connector                                 | Plastic, VISTAL®          |
| Weight   | Approx. 50 g              |
| Maximum tightening torque of the fixing screws | 1.3 Nm                    |

#### Ambient data

| Enclosure rating              | IP66 (EN 60529)<br>IP67 (EN 60529)<br>IP69 (EN 60529) <sup>1)</sup>   |
|-------------------------------|---|
| Ambient operating temperature | -40 °C +60 °C   |
| Ambient temperature, storage  | -40 °C +75 °C   |
| Shock resistance              | 50 g, 11 ms (25 positive and 25 negative shocks per axis, for X, Y, Z axes, 150 shocks in total (EN60068-2-27)) |

<sup>&</sup>lt;sup>1)</sup> Replaces IP69K with ISO 20653: 2013-03.

<sup>&</sup>lt;sup>2)</sup> Signal transit time with resistive load in switching mode.

<sup>3)</sup> With light/dark ratio 1:1.

|                                     | 50 g, $6$ ms (5,000 positive and 5,000 negative shocks per axis, for X, Y, Z axes, 30,000 shocks in total (EN60068-2-27)) |
|-------------------------------------|---|
| Vibration resistance                | 10 Hz 2,000 Hz (Amplitude 0.5 mm / 10 g, 20 sweeps per axis, for X, Y, Z axes, 1 octave/min, (EN60068-2-6))               |
| Air humidity                        | 35 % 95 %, Relative humidity (no condensation)  |
| Electromagnetic compatibility (EMC) | EN 60947-5-2  |
| Resistance to cleaning agent        | ECOLAB  |
| UL File No.                         | NRKH.E181493 & NRKH7.E181493  |

 $<sup>^{1)}</sup>$  Replaces IP69K with ISO 20653: 2013-03.

#### Smart Task

| Smart Task name                  | Base logics   |
|----------------------------------|---|
| Logic function                   | Direct AND OR Window Hysteresis                                     |
| Timer function                   | Deactivated On delay Off delay ON and OFF delay Impulse (one shot)  |
| Inverter                         | Yes   |
| Switching frequency              | SIO Logic: 800 Hz $^{1)}$ IOL: 650 Hz $^{2)}$                       |
| Response time                    | SIO Logic: 600 $\mu s^{1)}$ IOL: 750 $\mu s^{2)}$                   |
| Repeatability                    | SIO Logic: 300 $\mu$ s <sup>1)</sup> IOL: 400 $\mu$ s <sup>2)</sup> |
| Switching signal                 |   |
| Switching signal Q <sub>L1</sub> | Switching output  |
| Switching signal $ar{Q}_{L1}$    | Switching output  |

<sup>1)</sup> Use of Smart Task functions without IO-Link communication (SIO mode).

#### Classifications

| eCl@ss 5.0   | 27270904 |
|--------------|----------|
| eCl@ss 5.1.4 | 27270904 |
| eCl@ss 6.0   | 27270904 |
| eCl@ss 6.2   | 27270904 |
| eCl@ss 7.0   | 27270904 |
| eCl@ss 8.0   | 27270904 |
| eCl@ss 8.1   | 27270904 |
| eCl@ss 9.0   | 27270904 |
| eCl@ss 10.0  | 27270904 |
| eCl@ss 11.0  | 27270904 |
| eCl@ss 12.0  | 27270903 |

 $<sup>^{2)}\,\</sup>mbox{Use}$  of Smart Task functions with IO-Link communication function.


# WTL16P-2416112BA00 | W16

SMALL PHOTOELECTRIC SENSORS

| ETIM 5.0       | EC002719 |
|----------------|----------|
| ETIM 6.0       | EC002719 |
| ETIM 7.0       | EC002719 |
| ETIM 8.0       | EC002719 |
| UNSPSC 16.0901 | 39121528 |

#### Connection type

M12 male connector, 4-pin




#### Connection diagram

Cd-390


#### Characteristic curve

WTL16P-xxxxx1xx

Minimum distance in mm (y) between the set sensing range (x) and white background (90 % remission)



Example: Safe suppression of the background





Black object (6 % remission)
Set sensing range x = 200 mm
Needed minimum distance to white background y = 15 mm

- ① Black object, 6% remission factor
- ② Gray object, 18% remission factor
- 3 White object, 90% remission factor


#### Light spot size


#### Vertical






#### Horizontal





#### Sensing range diagram

#### WTL16P-xxxxx1xx



Recommended sensing range for the best performance

#### Adjustments


Display and adjustment elements



- ① LED indicator green
- ② LED indicator yellow
- ③ Teach-Turn adjustment
- 4 LED blue

#### Dimensional drawing (Dimensions in mm (inch))

WTB16, WTF16, WTL16, connector



- ① Standard direction of the material being detected
- ② Center of optical axis, sender
- ③ Center of optical axis, receiver
- 4 Mounting hole, Ø 4.1 mm
- ⑤ Connection
- ⑤ Display and adjustment elements

#### Recommended accessories

Other models and accessories  $\rightarrow$  www.sick.com/W16

|                              | Brief description   | Туре        | Part no. |  |  |
|------------------------------|---|-------------|----------|--|--|
| Universal bar clamp systems  |   |             |          |  |  |
|                              | Plate N02 for universal clamp bracket, Zinc plated steel (sheet), Zinc die cast (clamping bracket), Universal clamp (5322626), mounting hardware        | BEF-KHS-N02 | 2051608  |  |  |
| Mounting brackets and plates |   |             |          |  |  |
| V                            | Adapter for mounting W16 sensors in existing W14-2/W18-3 installations or L25 sensors in existing L28 installations, plastic, fastening screws included | BEF-AP-W16  | 2095677  |  |  |

# WTL16P-2416112BA00 | W16

## SMALL PHOTOELECTRIC SENSORS

|                            | Brief description   | Туре                   | Part no. |  |  |
|----------------------------|---|------------------------|----------|--|--|
| Plug connectors and cables |   |                        |          |  |  |
|                            | Head A: female connector, M12, 4-pin, straight, A-coded<br>Head B: Flying leads<br>Cable: Sensor/actuator cable, PVC, unshielded, 5 m | YF2A14-<br>050VB3XLEAX | 2096235  |  |  |
|                            | Head A: male connector, M12, 4-pin, straight Cable: unshielded  | STE-1204-G             | 6009932  |  |  |

## SICK AT A GLANCE

SICK is one of the leading manufacturers of intelligent sensors and sensor solutions for industrial applications. A unique range of products and services creates the perfect basis for controlling processes securely and efficiently, protecting individuals from accidents and preventing damage to the environment.

We have extensive experience in a wide range of industries and understand their processes and requirements. With intelligent sensors, we can deliver exactly what our customers need. In application centers in Europe, Asia and North America, system solutions are tested and optimized in accordance with customer specifications. All this makes us a reliable supplier and development partner.

Comprehensive services complete our offering: SICK LifeTime Services provide support throughout the machine life cycle and ensure safety and productivity.

For us, that is "Sensor Intelligence."

# **WORLDWIDE PRESENCE:**

Contacts and other locations -www.sick.com

