





The YLN connector adds variations in shape to the existing color variations of the YL connector in order to improve identification of connectors. Moreover, this connector has a mechanism to prevent incomplete mating by utilizing the inertial force generated when the plug and receptacle are mated and therefore, ensures complete mating.

- Design to prevent incidental mating with the YL connector
- Inertial force mechanism
- Interchangeability
- Finger friendly design

Specifications -

- Current rating: 10 A max. AC, DC
 - (7 A when retainers are mounted)
- Voltage rating: 300 V max. AC, DC
- Temperature range: -25°C to +90°C (including temperature rise in applying electrical current)
- Contact resistance: Initial value/ 7 m Ω max.
 - After environmental tests/ 10 m Ω max.
- Insulation resistance: $1,000 \text{ M}\Omega$ min.
- Withstanding voltage: 1,500 VAC/minute
- Applicable wire: AWG #26 to #16
 - 0.13 to 1.25 mm²
- * Refer to "General Instruction and Notice when using Terminals and Connectors" at the end of this catalog.
- * Contact JST for details.
- * Compliant with RoHS.

Note: The current rating differs depending on the number of circuits and the wire size used in each connector. The table below lists the current rating as a function of the number of circuits and the wire size.

					Currer	nt unit : A	
Circuits	Wire size (AWG)						
	#16	#18	#20	#22	#24	#26	
2	10	7	5	4	3	2	
3	9	6	4	4	3	2	
4	9	6	4	4	3	2	
6	8	5	3	3	2	2	

Note: Secondary retainers cannot be used with AWG #16 wires.

Standards

- Recognized E60389
- Certified LR20812
- A R9351052

Assembly layout

<2, 3 circuits>



<4, 6 circuits>



YLN CONNECTOR



Socket contact

Housing

2.8

<u>%</u>



14 2

4.4

Model No. Applicable wire Insulation O.D. Q'ty/ Pin contact Socket contact mm² AWG # (mm) reel SYM-01T-P0.5A SYF-01T-P0.5A 0.13~0.5 26~20 1.3~2.5 4,000 (SYM-01T-P0.5A) 0.5~1.25 $20 \sim 16$ $20 \sim 34$ 5,000 SYM-41T-P0.5A SYF-41T-P0.5A 0.3+0.3~ 22+22~ 1.5+1.5~ 0.5+0.5 20+20 2.0+2.0

Material and Finish

Phosphor bronze, tin-plated (reflow treatment)

RoHS compliance

Note: 1. Contact JST for special products.

2. Retainers cannot be used with electric wire whose insulation O.D. exceeds 2.7 mm and AWG #16.

Contact	Crimping machine	Applicator					
Contact		Crimp applicator	Dies	Crimp applicator with dies			
SYM-01T-P0.5A	AP-K2N	MKS-L	MK/SYF/M-01-05	APLMK SYF/M01-05			
SYF-01T-P0.5A		*MKS-SC-YL	SC/SYF/M-01-05	APLSC SYF/M01-05			
SYM-41T-P0.5A		MKS-L	MK/SYF/M-41-05	APLMK SYF/M41-05			
SYF-41T-P0.5A		*MKS-SC-YL	SC/SYF/M-41-05	APLSC SYF/M41-05			

Note: *Strip-crimp applicator

Material: Housing...PA 66, UL94V-0, natural (white) Retainer...Glass-filled PA 66, UL94V-0, natural (ivory)



RoHS compliance

Note: Current rating in parentheses is for use with AWG #16 wire. (Retainers are not mountable.)